

**47506050**

## Closed toroid 50mm DELTA IP50



### Strong points

- A complete range
- Number of fixing options (?IP and ?IP-R)
- Patented centring solution (?IP and ?IP-R)
- Quick to install and safe to use (?IP-R)

### General characteristics

- Full range.
- Number of fixing options (?IP and ?IP-R).
- Patented centring solution (?IP and ?IP-R).
- Quick to install and safe to use (?IP-R).

### Compliance with standards

- IEC 61869-1

### Access to resources (ex: manuals)

<https://www.socomec.co.in/en-in/reference/47506050>

You need core balance transformers to install fault detection and locating units. These enclose the active conductors and highlight earth fault currents. Socomec core balance transformers meet measurement sensitivity needs and are suitable for ISOM Digiware locating systems. Closed (?IP, WR and TFR series) or split (?IP-R series), both types are suitable for all wiring configurations. The use of the ISOM T-15 adapter is required to connect the core balance transformers to ISOM Digiware F-60.

<b>Classification</b>	
UNSPSC	39122309
ETIM Class	EC002048
IGCC	5343
<b>Commerce</b>	
Effective date	2011-07-04
Country of origin	FR
<b>ETIM - Electrical characteristics</b>	
Rated primary current [A]	10
Rated secondary current [A]	0.016
Rated secondary apparent power [VA]	0.02
Accuracy class	3
Overcurrent limiting factor	FS 5
Calibrated	No
<b>ETIM - Mechanical characteristics</b>	
With contact protection	No
Opening diameter [mm]	50
Snap mounting	Yes
With copper rail	No
Secondary connection	Plug-in connection
<b>ETIM - Technical features</b>	
Model	Other
Number of primary inputs	1
<b>Logistics</b>	
GTIN/EAN	3596032613815
Customs number	8504312990
Price unit	PC
Weight of the packing unit	0.36
Length of the packing unit	0.136
Width of the packing unit	0.136
Depth of the packing unit	0.054
<b>Norms</b>	
Conformity to standards	IEC
<b>Technical Characteristics</b>	
Model	DELTA IP 50
Opening	Circular closed
Size	50 mm